

SBP Series (AC-Coupled)

Single Phase AC Retrofit Storage Solution (LV Battery)



Technical Data		GW3600S-BP	GW5000S-BP
Battery Input Data	Battery Type* ¹	Li-Ion	
	Nominal Battery Voltage (V)	48	
	Max. Charging Voltage (V)	≤60 (Configurable)	
	Max. Charging Current (A)* ¹	75	100
	Max. Discharging Current (A)* ¹	75	100
	Battery Capacity (Ah)* ²	50~2000	
	Charging Strategy for Li-Ion Battery	Self-adaption to BMS	
AC Output Data (On-grid)	Nominal Power Output to Utility Grid (W)	3680	5000
	Max. Apparent Power Output to Utility Grid (VA)	3680	5000
	Max. Apparent Power from Utility Grid (VA)	7360	9200
	Nominal Output Voltage (V)	230	
	Nominal Output Frequency (Hz)	50/60	
	Max. AC Current Output to Utility Grid (A)	16	22.8* ³
	Max. AC Current from Utility Grid (A)	32	40
	Output Power Factor	~1 (Adjustable from 0.8 leading to 0.8 lagging)	
	Output THDi (@Nominal Output)	<3%	
	AC Output Data (Back-up)	Max. Output Apparent Power (VA)* ⁴	3680
Peak Output Apparent Power (VA)* ⁴		4416, 10sec	5500, 10sec
Automatic Switch Time (ms)		<10	
Nominal Output Voltage (V)		230 (±2%)	
Nominal Output Frequency (Hz)		50/60 (±0.2%)	
Max. Output Current (A)		16	22.8
Output THDv (@Linear Load)		<3%	
Efficiency	Max. Efficiency	95.5%	
Protection	Anti-Islanding Protection	Integrated	
	Output Over Current Protection	Integrated	
	Output Short Protection	Integrated	
	Output Over Voltage Protection	Integrated	
General Data	Operating Temperature Range (°C)	-25~60	
	Relative Humidity	0~95%	
	Operating Altitude (m)	4000	
	Cooling	Nature Convection	
	Noise (dB)	<25	
	User Interface	LED & APP	
	Communication with BMS* ⁵	RS485; CAN	
	Communication with Meter	RS485	
	Communication with Portal	Wi-Fi* ⁵	
	Weight (kg)	18.5	
	Size (Width*Height*Depth mm)	347*432*190	
	Mounting	Wall Bracket	
	Protection Degree	IP65	
	Standby Self-Consumption (W)	<15	
	Topology	Battery Isolation	

*¹: The actual charge and discharge current also depends on the battery.

*²: Battery capacity could be not less than 100Ah where the back-up function is to be applied.

*³: 21.7A is for AS4777.2.

*⁴: Can be reached only if battery capacity is enough, otherwise will shut down.

*⁵: CAN communication is configured by default. If 485 communication is used, please replace the corresponding communication line.

*: Please visit GoodWe website for the latest certificates.